

Chevrolet Camaro 1980 – 1981 fuse box diagrams

Fuse Box diagram



Chevrolet Camaro – fuse box diagram

No.	A	Circuit Protected
1	5	Instrument panel lights, alarm buzzer, heater dial light, radio dial and wiper switch light
2	20	Choke heater
3	–	–
4	30	<i>Circuit breaker:</i> Power windows and sunroof
5	–	–
6	25	Heater and air conditioning
7	10	Electronic Control Module
8	–	–
9	25	Windshield wipers
10	20	Stop light, hazard light
11	10	Cruise control, rear window defogger, fuel gauge, hood louvre, gauges, closed loop, warning lamps and buzzers and tailgate unlock.
12	20	Parking, side marker, license and tail lights, engine compartment light
13	10	Radio and idle stop solenoid
14	30	<i>Circuit breaker:</i> Power door locks, power seats, rear window defogger and tailgate lock
15	20	Back-up and turn signal lights
16	20	Luggage compartment light, cigar lighter, clock, glove box light, courtesy lights, key warning buzzer, closed loop, dome and reading lights
17	–	–
18	–	–
19	–	–

Circuit Breaker:

Headlights — Circuit breaker is integral with headlight switch to protect headlight circuit.

Windshield Wiper — Circuit breaker integral with windshield wiper switch to protect wiper circuit.

Power Seats, Power Windows & Power Door Locks — Circuit breaker is located on fuse panel to protect power accessories.

Rear Window Defogger – Circuit breaker is located on fuse panel to protect rear window circuit.